

HyLite OptiMax™ LED Tube have been tested for compatibility to work flawlessly with the Ballasts shown above. HyLite is continually testing OptiMax™ LED Tube on various other Ballasts. We will continue to update the Ballast Compatibility List as additional models are tested. Please contact HyLite about any Ballasts not shown on this list.

**Note:** Risk of Fire or Electric Shock. Before Installation, check Specifications for the most Current Ballast Compatibility List. If the Ballast model does not appear on this List, please **DO NOT** Install, until you check with HyLite. Installing Tube Lights without verifying it against the Ballast Compatible List and without testing the Compatibility will void all Warranties. If not Compatible, insert LED Tubes according to Type B Installation Instructions only. Read and Understand all Installation Instructions before installing HyLite OptiMax™ LED T8 Tube Lights.

Ballast Brand	Model No.	Start Type	Max Load Qty.	Compatible (Y/N)			
				1 Lamp	2 Lamps	3 Lamps	4 Lamps
ACT	ACT3P32ISUNVE	Instant Start	3	Y	Y	Y	N/A
ACT	ACT4P32ISUNVE	Instant Start	4	N	N/A	Y	Y
Damar	1688B	Instant Start	2	Y	Y	N/A	N/A
Damar	1688D	Instant Start	2	N	Y	N/A	N/A
Damar	3654C	Instant Start	3	N	Y	Y	N/A
EIKO	PM-2X32T8-UNV-IS	Instant Start	2	Y	Y	N/A	N/A
Espen	VE232MVHIPL	Instant Start	2	Y	Y	N/A	N/A
Espen	VE2P32MVHIPE 11068	Instant Start	2	Y	Y	N/A	N/A
Espen	VE2P32MVHIPHE 11069	Instant Start	2	N	Y	N/A	N/A
Espen	VE2P32MVHPPE 11080	Programmed Start	2	Y	Y	N/A	N/A
Espen	VE332MVHIPL	Instant Start	3	Y	Y	Y	N/A
Espen	VE3P32MVHIPL 11056	Instant Start	3	Y	Y	Y	N/A
Espen	VE3P32MVHIPE 11070	Instant Start	3	Y	Y	Y	N/A
Espen	VE3P32MVHPPE 11083	Programmed Start	3	Y	Y	Y	N/A
Espen	VE4P32MVHIPL 11057	Instant Start	4	Y	N/A	Y	Y
Espen	VE4P32MVHIPE 11072	Instant Start	4	N	N/A	Y	Y
Espen	VE4P32MVHPPE 11086	Programmed Start	4	Y	N/A	Y	Y
Fulham	FH12-UNV-1400L	Emergency	1	Y	N/A	N/A	N/A
GE	GE132MAX-G-N	Instant Start	1	Y	N/A	N/A	N/A
GE	GE132MAX-H/Ultra	Instant Start	1	Y	N/A	N/A	N/A
GE	GE132MAXP-L/ULTRA	Instant Start	1	Y	N/A	N/A	N/A
GE	GE132MAXP-N/ULTRA	Instant Start	1	Y	N/A	N/A	N/A
GE	GE-132-MV-N	Instant Start	1	Y	N/A	N/A	N/A
GE	GE-132-MV-PS-H	Programmed Start	1	Y	N/A	N/A	N/A
GE	GE-132-MV-PS-L	Programmed Start	1	Y	N/A	N/A	N/A
GE	GE232MAX-G-N	Instant Start	2	Y	Y	N/A	N/A
GE	GE232MAX-G-N-DILY	Instant Start	2	Y	Y	N/A	N/A
GE	GE232MAX-G-N-DIYB	Instant Start	2	Y	Y	N/A	N/A
GE	GE232MAX-H/ULTRA	Instant Start	2	Y	Y	N/A	N/A
GE	GE232MAX-L/ULTRA	Instant Start	2	Y	Y	N/A	N/A
GE	GE232MAXP-H/ULTRA	Instant Start	2	Y	N	N/A	N/A
GE	GE232MAXP-L/ULTRA	Instant Start	2	Y	Y	N/A	N/A
GE	GE-232-MV-N	Instant Start	2	Y	Y	N/A	N/A
GE	GE232-MVPS-L	Programmed Start	2	Y	Y	N/A	N/A
GE	GE232-MVPS-N	Programmed Start	2	Y	Y	N/A	N/A
GE	GE-232-MVPSN-V03	1-10V Dimming	2	Y	Y	N/A	N/A
GE	GE-232-MVPS-XL	Programmed Start	2	Y	Y	N/A	N/A
GE	GE232MAX-G-N	Instant Start	3	Y	Y	Y	N/A

Ballast Brand	Model No.	Start Type	Max Load Qty.	Compatible (Y/N)			
				1 Lamp	2 Lamps	3 Lamps	4 Lamps
GE	GE232MAX-G-N-DIYB	Instant Start	3	Y	Y	Y	N/A
GE	GE332MAXP-L/ULTRA	Instant Start	3	Y	Y	Y	N/A
GE	GE332MAXP-N/ULTRA	Instant Start	3	Y	Y	Y	N/A
GE	GE332MV-N-DIY	Instant Start	3	Y	Y	Y	N/A
GE	GE332-MVPS-L	Programmed Start	3	Y	Y	Y	N/A
GE	GE-332-MVPS-XL	Programmed Start	3	Y	Y	Y	N/A
GE	GE432MAX-G-N	Instant Start	4	N	N/A	Y	Y
GE	GE432MAXG-N-DIYL	Instant Start	4	N	N/A	Y	Y
GE	GE432MAX-L/Ultra	Instant Start	4	Y	N/A	Y	Y
GE	GE432MAXP347-N	Instant Start	4	Y	N/A	Y	Y
GE	GE432MAXP-H/ULTRA	Instant Start	4	N	N/A	N	Y
GE	GE432MAXP-L/ULTRA	Instant Start	4	Y	N/A	Y	Y
Halco	EP232IS/MV/HE	Instant Start	2	Y	Y	N/A	N/A
Halco	EP332IS/MV/HE	Instant Start	3	Y	Y	Y	N/A
Halco	EP332IS/L/MV/HE	Instant Start	3	Y	Y	Y	N/A
Halco	EP432IS/L/MV/HE	Instant Start	4	Y	N/A	Y	Y
Howard	EP2/32IS/MV/MC/HE	Instant Start	2	Y	Y	N/A	N/A
Howard	EPL2/32IS/MV/MC/HE	Instant Start	2	Y	Y	N/A	N/A
Howard	EPL3/32IS/MV/SC/HE	Instant Start	3	Y	Y	Y	N/A
Howard	EP4/32IS/MV/MC/HE	Instant Start	4	N	N/A	Y	Y
Howard	EPL4/32IS/MV/MC/HE	Instant Start	4	Y	N/A	Y	Y
Keystone	KTEB-232-UV-IS-N-P	Instant Start	2	Y	Y	N/A	N/A
Keystone	KTEB-332-UV-IS-N-P	Instant Start	3	Y	Y	Y	N/A
Keystone	KTEB-432-UV-IS-N-P	Instant Start	4	N	N/A	Y	Y
Keystone	KTEB-432RIS-1-TP-SL	Instant Start	4	Y	N/A	Y	Y
Keystone	KT-EMRG-1400	Emergency	2	Y	Y	N/A	N/A
Keystone	KT-EMRG-500-SL	Emergency	1	Y	N/A	N/A	N/A
Philips	ICN-2P32-N	Instant Start	2	N	Y	N/A	N/A
Philips	ICN-2P32-SC	Instant Start	2	Y	Y	N/A	N/A
Philips	ICN-4P32-SC	Instant Start	4	N	N/A	Y	Y
Philips	IOP-4P32-LW-N	Instant Start	4	Y	N/A	Y	Y
Philips	REL-2P32-SC	Instant Start	2	Y	N	N/A	N/A
Philips	RCN-2S32-SC	Instant Start	2	N/A	Y	N/A	N/A
Philips	REL-4P32-RH-TP	Instant Start	4	N	N/A	Y	Y
Philips	ICN-2P32-SC	Instant Start	2	Y	Y	N/A	N/A
Philips	ICN-4P32-N	Instant Start	4	N	N/A	Y	Y
Philips	IOP-2P32-HL-N	Instant Start	2	N	Y	N/A	N/A
Philips	IOP-2P32-LW-N	Instant Start	2	Y	Y	N/A	N/A
Philips	IOP-2P32-N	Instant Start	2	Y	Y	N/A	N/A
Philips	IOP-2PSP32-LW-N	Programmed Start	2	Y	Y	N/A	N/A
Philips	IOP-2PSP32-N	Programmed Start	2	Y	Y	N/A	N/A
Philips	IOP-4P32-LW-N	Instant Start	4	Y	N/A	Y	Y
Philips	IOP-4PSP32-LW-SC	Programmed Start	4	Y	N/A	Y	Y
Philips	IOP-4PSP32-SC	Programmed Start	4	N	N/A	Y	Y

Ballast Brand	Model No.	Start Type	Max Load Qty.	Compatible (Y/N)			
				1 Lamp	2 Lamps	3 Lamps	4 Lamps
Philips	IOPA-1P32-LW-N	Instant Start	1	Y	N/A	N/A	N/A
Philips	IOPA-2P32-LW-N	Instant Start	2	Y	Y	N/A	N/A
Philips	IOPA-2P32-N	Instant Start	2	N	Y	N/A	N/A
Philips	IOPA-3P32-LW-N	Instant Start	3	Y	Y	Y	N/A
Philips	IOPA-3P32-LW-SC	Instant Start	3	Y	Y	Y	N/A
Philips	IOPA-3P32-N	Instant Start	3	N	N	Y	N/A
Philips	IOPA-4P32-N	Instant Start	4	N	N/A	Y	Y
Philips	IZT-2S32-SC	1-10V Dimming	2	Y	Y	N/A	N/A
Philips	RCN-2S32-SC	Instant Start	2	N	Y	N/A	N/A
Philips	REL-2P32-SC	Instant Start	2	N	Y	N/A	N/A
Philips	REL-4P32-RH-TP	Instant Start	4	N	N/A	Y	N
Philips	REZ-2S32-SC	Triac Dimming	2	Y	Y	N/A	N/A
Philips	VEL-4P32-SC	Instant Start	4	N	N/A	Y	Y
Plusrite	BAF232IS/MV	Instant Start	2	N	Y	N/A	N/A
Plusrite	BAF332IS/MV	Instant Start	3	Y	Y	Y	N/A
Plusrite	BAF432IS/MV	Instant Start	4	N	N/A	Y	Y
Robertson	IEA432T8120N 3P20135	Instant Start	4	Y	N/A	Y	Y
Sunlite	40155-SU-SB/232/MV	Instant Start	2	Y	Y	N/A	N/A
Sylvania	QHE 1x32T8/UNV ISH HT SC	Instant Start	1	Y	N/A	N/A	N/A
Sylvania	QHE 1X32T8/UNV ISN-SC	Instant Start	1	Y	N/A	N/A	N/A
Sylvania	QHE 2X32T8/347 ISL-SC	Instant Start	2	Y	Y	N/A	N/A
Sylvania	QHE 2x32T8/UNV ISL-SC	Instant Start	2	Y	Y	N/A	N/A
Sylvania	QHE 2X32T8/UNV ISL-SC-1	Instant Start	2	Y	Y	N/A	N/A
Sylvania	QHE 2x32T8/UNV ISN-SC	Instant Start	2	Y	Y	N/A	N/A
Sylvania	QHE 2X32T8/UNV PSN-MC	Programmed Start	2	Y	Y	N/A	N/A
Sylvania	QHE 3X32T8/UNV PSN-MC	Programmed Start	3	Y	Y	Y	N/A
Sylvania	QHE 3x32T8/UNV ISL-SC	Instant Start	3	Y	N/A	Y	N/A
Sylvania	QHE 3XLEDT8/UNV-ISN-SC	Instant Start	3	Y	N/A	Y	N/A
Sylvania	QHE 4x32T8/UNV ISL-SC	Instant Start	4	Y	N/A	Y	Y
Sylvania	QHE 4x32T8/UNV ISN-SC	Instant Start	4	N	N/A	Y	Y
Sylvania	QHE 4xLEDT8/UNV-ISN-SC	Instant Start	4	N	N/A	N/A	Y
Sylvania	QTP 1X32T8/UNV ISN-SC	Instant Start	1	Y	N/A	N/A	N/A
Sylvania	QTP 3X32T8/UNV ISN-SC	Instant Start	3	Y	Y	Y	N/A
Sylvania	QTP 4X32T8/UNV ISN-SC	Instant Start	4	N	N/A	Y	Y
UltraSave	UT232347	Instant Start	2	Y	Y	N/A	N/A
Universal	B232IUNVEL-N	Instant Start	2	Y	Y	N/A	N/A
Universal	B232IUNVHP-N	Instant Start	2	Y	Y	N/A	N/A
Universal	B232PUNVHE-B	Programmed Start	2	Y	Y	N/A	N/A
Universal	B332IUNVEL-A	Instant Start	3	Y	Y	Y	N/A
Universal	B332IUNVHE-A	Instant Start	3	Y	Y	Y	N/A
Universal	B332IUNVHP-A	Instant Start	3	Y	Y	Y	N/A
Universal	B432IUNVHE-A	Instant Start	4	N	N/A	Y	Y
Universal	B432IUNVHP-A	Instant Start	4	Y	N/A	Y	Y
Universal	B432PUNVHE-A	Programmed Start	4	N	N/A	Y	Y
Universal	B232IUNV-C	Instant Start	2	Y	Y	N/T	N/T